

Содержание

Добавление программы в автозагрузку	3
---	---

Добавление программы в автозагрузку

Для добавления программы в автозагрузку, необходимо добавить в каталог `buildroot/board/rockchip/px30/fs-overlay-64/etc/init.d` при сборке, при прошивке `burn/add_for_burn_sd/upper/etc/init.d`, либо на готовой флешке в каталог `/etc/init.d/`, в разделе на 1ГБ, скрипт запуска вашего приложения, примерный код запуска с weston приведен ниже.

Пользовательский скрипт нужно назвать в формате «S99...». Если у вас уже запущен weston, то его не надо запускать второй раз.

```
#!/bin/sh
#
# Application description ...
#

# Load default env variables from profiles(e.g.
/etc/profile.d/weston.sh)
. /etc/profile

case "$1" in
    start)

        export XDG_RUNTIME_DIR=${XDG_RUNTIME_DIR:-/var/run}
        export QT_QPA_PLATFORM=${QT_QPA_PLATFORM:-wayland}

        weston --tty=2 --idle-time=0&
        {
            # Wait for weston ready
            while [ ! -e ${XDG_RUNTIME_DIR}/wayland-0 ]; do
                sleep .1
            done
            **ЗАПУСК ВАШЕГО ПРИЛОЖЕНИЯ**
        }&
        ;;
    stop)
        **ОСТАНОВКА ВАШЕГО ПРИЛОЖЕНИЯ**
        ;;
    *)
        echo "Usage: $0 {start|stop}"
        exit 1
        ;;
esac
exit 0
```

Пример скрипта:

```
#!/bin/sh
#
```

```
#

. /etc/profile

case "$1" in
    start)

        export XDG_RUNTIME_DIR=${XDG_RUNTIME_DIR:-/var/run}
        export QT_QPA_PLATFORM=${QT_QPA_PLATFORM:-wayland}

        # Wait for weston ready
        while [ ! -e ${XDG_RUNTIME_DIR}/wayland-0 ]; do
            sleep .1
        done
        /mnt/store/a7server/app&
        ;;
    stop)
        killall app
        ;;
    *)
        echo "Usage: $0 {start|stop}"
        exit 1
        ;;
esac
exit 0
```